



PRAISTON Sp. z o.o.
ul. Górowska 32
64-100 Leszno
Polska

Biuro: +48 65 527 01 67
Serwis: +48 782 844 000
Fax: +48 65 527 01 67

E-mail: biuro@praiston.pl

Koordinator ds. sprzedaży
Krzysztof Wybieralski
+48 882 762 006

kw@praiston.pl



Infusion pump FRESNIUS INJECTOMAT 2000 DIN (Reconditioned)

Used,
Technical condition: very good,
Visual condition: very good,
French production,
Emergency power supply: 230 V,
Emergency power supply: via a new 1 built-in 6 V 1.1/1.3 Ah battery
Frequency: 50/60 Hz,
Power: 23 VA,

The Injectomat 2000 is a syringe-operated, single-channel infusion pump for the precise dosing of fluids,

Syringes supported:

20 mL - PERFUSOR, OMNIFIX, INJECTOMAT,

50 mL - PERFUSOR, OMNIFIX, INJECTOMAT,

Easy to read digital LED display,

Visual and acoustic alarms,

Syringe size reader,

Programmable drug name,

Automatic bolus reduction after release of occlusion,

Quick start,

Equipped with RS-232 socket for computer connection,

Comfortable carrying handle,

Foiled control panel,

English language keyboard on the control panel,

Specifications:

Delivery speed: 0.1 - 200 ml / h,

Bolus: 50 - 500 mL / h,

Infusion volume: 0.1 - 999 mL,

KVO: 1 mL / h,

Occlusion pressure (for 50/60 mL syringe):

Low: 300 mmHg,

Medium: 525 mmHg,

High: 900 mmHg,

Feeding accuracy: $\pm 3\%$,

Pause: 1min - 9 h 59 min, step 1 min,

Included:

Operating manual in German (PDF),

Power cord,

Dimensions: 32.5 x 19 x 12 cm,

Weight: 2.5 kg,

Comes with a current Technical Passport issued,

Warranty:

6 months for domestic market - Poland,

1 month for the international market,

Financing options (Poland only): Installments, Leasing, Loan,

If you have any questions, please do not hesitate to contact us!

In case you don't find the product you are interested in, please get in touch with us and we will do our best to find the perfect solution for YOU.

WE SPEAK ENGLISH

HABLAMOS ESPANOL

WIR SPRECHEN DEUTSCH

ON PARLE FRANCAIS

WIJ SPREKEN NEDERLANDS

МЫ ГОВОРИМ ПО РУССКИ

МИ РОЗМОВЛЯЄМО УКРАЇНСЬКОЮ

WE SHIP WORLDWIDE

